

Media & CCTV LCD Monitor

Model No. LR804

8.0" TFT LCD Colour Video Security & Media Monitor, 4 CH Camera Multiplexer with DVR, with separate simultaneous function Media player via DVD player or SD Card reader to internal or external Monitor. LR804D includes a 500Gb disk drive.



The LR804 is an amazing compact unit, with 2 separate simultaneous independent functions Security and Media Playback. The first is an 8.0" LCD Monitor, 4 Channel Mjpeg camera input with Multiplex, DVR (via hard disc not supplied) or via External Storage USB. With 4 channel Alarm function. The second is a Media Playback unit from the internal DVD player or SD Card reader with Media output (Video & Audio) to the internal or external monitor. Easy access draw for Hard Disc drive. Mouse input via USB or PS2. Backup to external unit via USB port. Multi language. Easy grip carry handle. All mounted in a Smart tough Aluminium Metal casing. This compact unit is ideal for CCTV Multimedia Video and Surveillance systems applications. This unit is Ideal for shops or small units. Can be networked to make larger systems. LR804 is supplied without Hard Disc Drive.

SPECIFICATIONS:

Monitor:

- High resolution 480,000 pixels 800x600.
- Active area: 480 x 306 (WxH) mm.
- PAL & NTSC & SECAM Auto.
- Viewing angle: L/R/U/D: 70/70/70/70°.
- Brightness 250 cd/m2, Contrast Ratio: 500:1. Picture Ratio: 4:3

DVR Function:

- Video: MJPEG, 4CH, 720 x 288.
- PTZ Control: Pan, Tilt, Zoom by Mouse.
- Display: Full, 4 split, PIP, Sequence, Digital Zoom. Speed: 25 FPS.
- Rec rate: 100 FPS. Mode: Cyclic, Motion, Schedule, Alarm. Quality: Low, Norm, High.
- Playback: Search: Percent, Time/Date, Event. Speed: Forward & Backwards: 1X, 2X, 4X, 8X, 16X, 32X, 1/2X, 1/4X, 1/8X, 1/16X.

Standard Accessories

- AC adapter + Lead
- PS2 Mouse, User CD
- I/R Remote Control
- A/V Lead Phono
- 3.5mm to Phono Lead
- BNC to Phono plug
- Hard Disc Screws x 4

All information correct at time of going to press. Design and specification are subject to change without prior notice. E&EO.

Model No. LR804 Continued.

- Alarm: I/P: 4 x NO/NC selectable, O/P: 1 x N/C. Mode: Video Loss, Duration 1-99 secs.
Event spot: Switching interval, Alarm, Motion and Event Pop-up.
- Remote: Web Viewer: Live, Playback, Backup, Setting, PTZ control. Network: Ethernet TCP/IP.
- User interface: RS485 PTZ camera control, USB mouse & External storage, Network RJ45.

Media Player:

- SD Card Reader storage: VCD, SVCD, MP3, CDDA, HDCD, CDG, WMA, JPEG, MPEG-1,2,4.
- DVD Player.

Audio/Video Interface:

- Video input: Camera x 4. Format: PAL or NTSC auto. Video output: Monitor and Spot.
Media out: Video & Audio via Phono from SD card or DVD. Audio Output via Speakers.

General:

- Front Controls: Down, Up, Menu, Source, On LED, Display, I/R Sensor.
- Power Source: 12V DC, 5.0 Amp, 60 Watts approx.
- Dimensions:-Unit: 193 x 182 x 198. Carton: 265 x 300 x 265 (WxHxD)mm.
- Finished in Black. Weight:- Unit: 2.97 kgms. Carton: 4.32 kgms.

Connections: Camera x 4 BNC. Monitor: BNC. Spot: BNC. Mouse: USB & PS2. Ethernet: RG45.
External Backup: USB. Media out: Audio 3.5mm, Video: Phono. PTZ control: 9 pin D-Sub.
Alarm: 10 pin Push connector. DC Input via 2.1 MM Socket.

- All information correct at time of going to press. Design and specification are subject to change without prior notice. E&EO.